




DT-3808

Light Meter with PC Interface DT-3808 light meter provide accurate display light level in terms of Foot Candles (FC) or LUX over wide range. Just turning the Function Switch to select the “lux” scale and setting the range to desired range, then removing the photo detector to light source in a horizontal position and reading the illuminance norminal from the LCD display. When the measurement is completed, replace the photo detector from the light source.



Features	
4000 Counts LCD dual display with timer function	
Auto Ranging	
Max./Min. and Data Hold	
Auto Power Off	
Low battery indication	
User selectable FC/Lux	
USB interface	
Capacity for data logging (99 readings)	
Total accuracy: for C.I.E standard illuminate A(2856K)	


Specifications	
Max Range	400,000Lux
Accuracy	$\pm 5\% \pm 10d (< 10,000\text{Lux})$ $\pm 10\% \pm 10d (> 10,000\text{Lux})$
Max Resolution	0.1Lux/0.01Fc
Measuring rate	1.5 times/second
Photo Detector	115mm x 60mm x 27mm




CE

Light Meter with PC Interface

DT-3808 light meter provide accurate display light level in terms of Foot Candles (FC) or LUX over wide range. Just turning the Function Switch to select the "lux" scale and setting the range to desired range, then removing the photo detector to light source in a horizontal position and reading the illuminance normal from the LCD display. When the measurement is completed, replace the photo detector from the light source.





Size(HxWxD): 160mm x 58mm x 27mm

Weight: 280g

Accessories : 9V battery, Photo Detector and USB cable, software, Carrying case and Gift box.