



Model 8516

8516 light meter provides accurate display light level in terms of Foot Candles FC or LUX over wide range. Just turning the Function Switch to select the “lux” scale and setting the range to desired range, then removing the light detector to light source in a horizontal position and reading the illuminance normal from the LCD display. When the measurement is completed, replace the light detector from the light source.

Features

- 2.4" TFT color display
- Auto Ranging
- Max/Min/AVG function
- Auto Power Off
- Low battery indication
- Selectable FC/Lux unit
- Capacity for data logging (99 readings)
- Total accuracy: for C.I.E standard illuminate A(2856K)
- Bluetooth interface with Smart phone APP

Specifications

Measuring range	400,000Lux
Accuracy	±5%±10d(<10,000Lux) ±10%±10d(>10,000Lux)
Max Resolution	0.1Lux/0.01Fc
Bluetooth interface	*

Size(HxWxD): 185mm x 68mm x 45mm

Weight: 248g

Accessories :

3.7V Li-battery, USB cable, software, Carrying case and Gift box.

