



DT-3368T/3369T-BT

1000A AC, AC/DC Clamp Meters

3360/3361/3363/3366/3367/3368 series professional 1000A AC, AC/DC clamp meters provide multi-function for 1000A AC, AC/DC, voltage, resistance, capacitance, Frequency, Temperature, duty cycle and continuity. These series are with 6000 / 6600 counts digital LCD display and analog bargraph.

Double molded housing

Electronic overload protection

Auto Power Off



| Specifications | | | | |
|------------------|--|----------------|-----------------|-------------|
| Function | Max. Range | Basic Accuracy | Max. Resolution | DT-3369T/BT |
| Current DC | 1000A | ±(2.5%+5d) | 1mA | * |
| Current AC | 1000A | ±(3.0%+4d) | 10mA | * |
| Voltage DC | 600V | ±(0.8%+2d) | 0.1mV | * |
| Voltage AC | 600V | ±(1.0%+4d) | 0.1mV | * |
| Resistance | 60MΩ | ±(1.0%+4d) | 0.1Ω | * |
| Capacitance | 4000μF | ±(3.0%+5d) | 0.01nF | 6000μF |
| Frequency | 10MHz | ±(1.2%+3d) | 0.001Hz | * |
| Duty Cycle | 99.90% | ±(1.2%+3d) | 0.10% | * |
| Temperature | 1000°C/1832°F | ±(3.0%+3d) | 0.1°C/°F | * |
| Inrush Current | 1000A | 0.1A | ±(2.0%+5d) | * |
| Continuity check | Threshold 40Ω, test current <0.5mA | | | |
| Diode test | Test current of 0.3mA typical, open circuit voltage <3V DC typical | | | |

| Features | DT-3368T | DT-3369T/BT |
|---------------------------------|----------|-------------|
| Digital display counts | 6600 | 6600 |
| Analog Bargraph/Segments | */60 | */60 |
| Electronic overload protection | * | * |
| Continuity buzzer & Diode check | * | * |
| Data Hold function | * | * |
| DCA Zero function | * | * |
| Min/Max Hold function | * | * |
| Auto Power Off | * | * |
| Low battery indication | * | * |
| AC/DC Current | * | * |
| True RMS measurements | * | * |
| 1.2"(30mm) Clamp jaw opening | | * |
| Inrush current function | * | * |
| Peak Voltage function | | * |
| Bluetooth interface | * | * |

Size(HxWxD): 229mm x 80mm x 49mm

Weight: 303g

Accessories: Test leads, gift box with carrying case, 9V battery, Temperature probe(3368/3369T-BT)