



# DT-3390/3391/3392/395/

## 1000A AC, AC/DC Clamp Meters

DT-3391/3392/3395/3397 Series Professional True RMS Clamp Meters provide accurate AC, AC/DC Current and Voltage readings regardless of waveforms. These meters can be used in most industrial and commercial applications where non-linear loads distort the Current or Voltage waveform.



EMC & LVD  
EN: 61326  
EN: 61010-1,  
EN: 61010-02-031





<b>Specifications</b>							
<b>Function</b>	<b>Max Range</b>	<b>Basic Accuracy</b>	<b>Max. Resolution</b>	<b>DT-3390</b>	<b>DT-3391</b>	<b>DT-3392</b>	<b>DT-3395</b>
<b>AC Current</b>	<b>1000 A</b>	<b>±(2.5%+5d)</b>	<b>10mA</b>	*	*	*	*
<b>DC Current</b>	<b>1000 A</b>	<b>±(3.0%+4d)</b>	<b>10mA</b>			*	*
<b>AC Voltage</b>	<b>600V</b>	<b>±(0.8%+2d)</b>	<b>0.1mV</b>	*	*	*	*
<b>DC Voltage</b>	<b>600V</b>	<b>±(1.0%+4d)</b>	<b>0.1mV</b>	*	*	*	*
<b>Resistance</b>	<b>40MΩ</b>	<b>±(1.0%+4d)</b>	<b>0.1Ω</b>	*	*	*	*
<b>Capacitance</b>	<b>40mF</b>	<b>±(3.0%+5d)</b>	<b>0.01nF</b>	<b>100μF</b>	<b>100μF</b>	*	<b>4000μF</b>
<b>Frequency</b>	<b>10MHz</b>	<b>±(1.2%+3d)</b>	<b>0.01MHz</b>	*	*	<b>4kHz</b>	*
<b>Temperature</b>	<b>1000°C/1832°F</b>	<b>±(3.0%+5d)</b>	<b>1°C/°F</b>		*	*	*

**Size (H x W x D): 271mm x 100mm x 47mm**

**Weight: 508g**

<b>Features</b>	<b>DT-3390</b>	<b>DT-3391</b>	<b>DT-3392</b>	<b>DT-3395</b>
<b>True RMS measurements</b>		*	*	*
<b>Digital display counts</b>	<b>4000</b>	<b>4000</b>	<b>4000</b>	<b>6000</b>
<b>Electronic overload protection</b>	*	*	*	*
<b>Analog Bargraph/segments</b>			<b>*/41</b>	<b>*/61</b>
<b>Continuity buzzer &amp; Diode check</b>	*	*	*	*
<b>Data Hold function</b>	*	*	*	*
<b>Peak Hold function</b>			*	<b>Min./Max.</b>
<b>Inrush current measurement</b>				
<b>DCA Zero function</b>			*	*
<b>Auto Power Off</b>	*	*	*	*
<b>Low battery indication</b>	*	*	*	*
<b>AC/DC Current</b>	<b>AC</b>	<b>AC</b>	*	*
<b>2" (52mm) Clamp jaw opening</b>	*	*	*	*
<b>NCV Detection</b>	*	*	*	*

# Applications

	<p><b>1000A AC, AC/DC Clamp Meters</b></p> <p>DT-3391/3392/3395/3397 Series Professional True RMS Clamp Meters provide accurate AC, AC/DC Current and Voltage readings regardless of waveforms. These meters can be used in most industrial and commercial applications where non-linear loads distort the Current or Voltage waveform.</p>
	 <ul style="list-style-type: none"><li>• 1000A True RMS</li><li>• Peak Hold Function(3392/3392W/3392BT)</li><li>• Inrush Current Measurement(3397)</li></ul>

**Accessories:** Test leads, gift box with carrying case, 9V battery and Temperature probe (3391/3391W/3392/3392W/3392BT/3395/3397)