

Cat.No. **7760-00**

## 3-Cup Anemometer

Install the 3-cup anemometer outdoor. Connecting the sensor and the indicator with a cable, instantaneous wind speed can be monitored indoor. Self generated power.



### Specifications

Type	3-cup anemometer
Measuring range	2 to 60 m/sec.
Transducer	AC generator
Starting speed	2 m/sec.
Power requirements	Self-generated
Withstand wind speed	80 m/sec.
Accuracy	±0.5 m/sec. below 10 m/sec. ±5% above 10 m/sec.
Cup size	100 mm dia.
Construction	Brass
Two conductor cable	Ø10 m (0.5 mm <sup>2</sup> )
Dimensions & weight (approx.)	Sensor: 380 (H) x 310 mm (1.9 kg) Indicator: 180 (W) x 190 (H) x 130 (D) mm (1.7 kg)

