



MODEL CI-50

50 AMPS CURRENT INTERRUPTER

FEATURES:

- **Interrupt AC or DC**
- **ON / OFF 0.1 sec to 99.9 sec**
- **Cable With Locking Connector**
- **LEDs show OPEN / CLOSED**
- **View Program shows cycle settings**
- **Battery operated (AA batteries)**
- **Easy to Operate / Program**
- **Cable Storage In Case**
- **Tan Colored Lockable Case Blends Into Surroundings**

**AVAILABLE
FROM STOCK**



Distributed by:

teststations.com

detectron.com

Info@tinker-rasor.com | tinker-rasor.com

Tinker & Razor quality is found in our products, our people and our customer service.

TINKER & RASOR

PRODUCT DATA SHEET | MODEL CL-50 CURRENT INTERRUPTER

FEATURES:

- Interrupt AC or DC side of the rectifier
- No polarity concerns
- 0.1s- 99.9s programming (0.1 sec increments)
- Highly Accurate Internal Clock
- LEDs show OPEN and CLOSED condition during operation
- Battery operated (AA)
- Battery life up to 100 hours
- Low battery indication

CONSTRUCTION:

- Solid state circuitry, no mercury relays
- Hard plastic resin case with strong lid latches Lock case with lid locked or able to open
- Low profile tan color
- Case includes internal storage area
- Easy to read, high contrast panel

APPLICATIONS:

- Interruption of CP rectifiers
- DCVG
- Pipe to Soil Potential
- Instant OFF
- Other potential readings

SPECIFICATIONS:

- 50 Amp max, AC or DC
- 120 Volt max, AC or DC
- (4) "AA" Batteries
- Starts in Open condition
- -19'C to 60'C (-2'F to 140'F)

DIMENSIONS:

5.75" x 12.25" x 10", 5 lbs
(146mm x 311mm x 254mm, 2.27 kg)

SHIPPING DIMENSIONS:

14" x 12" x 6", 6 lbs

DELIVERY: **Immediately from STOCK**
F.O.B. New Braunfels, TX USA

SERVICE: **24-hour Turn-Around**

TERMS: Net 30 Days, on approval of credit

WARRANTY: **90 Days**, parts and labor



Easy to use and operate, the CI-50 can be programmed in seconds and interrupting immediately.



The small panel size of the CI-50 allows for a large amount of storage room inside the case.

The case can also be locked.



The CI-50 uses AA batteries. Easy to find and easy to replace.

The AA batteries in the CI-50 will keep it operating for more than 80 hours.



The CI-50 Interrupter comes with the cable included. The single, locking connector leads to a pair of booted clamps. Cable length is 6' (1.8m) (p/n: 026-085)

AVAILABLE FROM STOCK

tinker-rasor.com